

Some Rnet's have 14 pins and some have 16 pins, first verify which one you need and use the following chart to decide the proper model you need. These parts can be ordered from www.mouser.com.

Crossover Frequency (Hz)	14 pin Rnet Mouser part number	16 pin Rnet Mouser part number
18800	71-MDP1403- 1K	71-MDP1603- 1K
15667	71-MDP1403- 1.2K	71-MDP1603- 1.2K
12533	71-MDP1403- 1.5K	71-MDP1603- 1.5K
10444	71-MDP1403- 1.8K	71-MDP1603- 1.8K
9400	71-MDP1403- 2K	71-MDP1603- 2K
8545	71-MDP1403- 2.2K	71-MDP1603- 2.2K
6963	71-MDP1403- 2.7K	71-MDP1603- 2.7K
5697	71-MDP1403- 3.3K	71-MDP1603- 3.3K
4821	71-MDP1403- 3.9K	71-MDP1603- 3.9K
4000	71-MDP1403- 4.7K	71-MDP1603- 4.7K
3686	71-MDP1403- 5.1K	71-MDP1603- 5.1K
3357	71-MDP1403- 5.6K	71-MDP1603- 5.6K
2765	71-MDP1403- 6.8K	71-MDP1603- 6.8K
2293	71-MDP1403- 8.2K	71-MDP1603- 8.2K
1880	71-MDP1403- 10K	71-MDP1603- 10K
1567	71-MDP1403- 12K	71-MDP1603- 12K
1253	71-MDP1403- 15K	71-MDP1603- 15K
1044	71-MDP1403- 18K	71-MDP1603- 18K
940	71-MDP1403- 20K	71-MDP1603- 20K
855	71-MDP1403- 22K	71-MDP1603- 22K
696	71-MDP1403- 27K	71-MDP1603- 27K
570	71-MDP1403- 33K	71-MDP1603- 33K
482	71-MDP1403- 39K	71-MDP1603- 39K
400	71-MDP1403- 47K	71-MDP1603- 47K
369	71-MDP1403- 51K	71-MDP1603- 51K
276	71-MDP1403- 68K	71-MDP1603- 68K
229	71-MDP1403- 82K	71-MDP1603- 82K
188	71-MDP1403- 100K	71-MDP1603- 100K
157	71-MDP1403- 120K	71-MDP1603- 120K
125	71-MDP1403- 150K	71-MDP1603- 150K
104	71-MDP1403- 180K	71-MDP1603- 180K
94	71-MDP1403- 200K	71-MDP1603- 200K
85	71-MDP1403- 220K	71-MDP1603- 220K
57	71-MDP1403- 330K	71-MDP1603- 330K
48	71-MDP1403- 390K	71-MDP1603- 390K
40	71-MDP1403- 470K	71-MDP1603- 470K
37	71-MDP1403- 510K	71-MDP1603- 510K
34	71-MDP1403- 560K	71-MDP1603- 560K
28	71-MDP1403- 680K	71-MDP1603- 680K
23	71-MDP1403- 820K	71-MDP1603- 820K
19	71-MDP1403- 1M	71-MDP1603- 1M